

Product Line
FORTIRACK

Type
RM-FR-T18
RM-FR-T18I

Supported Models **FORTIGATE 80F-POE**

DIMENSIONS 2U

COLOR RAL 9003 White

PRODUCT DIMENSIONS 89 x 482 x 217 mm

(height x width x depth) 3.50 x 18.98 x 8.54 in



MOUNTING INSTRUCTIONS

- Optional: Remove the metal circles on the front of the rack with a screwdriver and a hammer and connect the pigtails from the back of the FortiRack to the round holes. Pigtails not provided.
- Place up to 2 power supplies on the rack.
- To install the power supplies, put the zip ties through the designated holes, place the power supplies on the rack between the zip ties and tighten firmly.
- Tie the excess length of the power cable(s) down with the zip tie(s).
- Remove the 4 rubber feet from the bottom of the FortiGate.
- Place your FortiGate on the rack & fix the FortiGate with the 2 bolts on the bottom and tighten them lightly.
- Connect the cables from your FortiGate to the connectors.
- Optional: use fiber patch cables (not supplied) to connect the SFP ports with fiber keystones.
- Optional: use two zip ties to hold the cables together.
- Place your FortiRack in your 19 inch rack.

Please ensure proper ventilation according to the network appliance manufacturer guidelines.

PACKAGE CONTENTS

Qty	Description
1	FortiRack + RJ45 / Fiber / USB coupler
9	Zip ties
2	Bolts M3x6mm
12	Cables - 0.5 meter

Fiber patch cable is not supplied due to the variety of fiber patch cables
Industrial version is supplied with shielded couplers and cables



**Consider the environment,
recycle where applicable.**

Rackmount.IT rack mount kits are RoHS compliant, developed & manufactured in the Netherlands and made of first quality parts.

In case of problems please contact your reseller or sales@rackmount.it.

Revision 2 - 11-04-2023

EMEA Office
Nonneveld 27
4811 HN Breda
The Netherlands
T +31 76 200 37 40
E sales@rackmount.it
WWW.RACKMOUNT.IT

US Office
9201 Metric Blvd - Unit A
Austin - TX 78758
United States
T +1 512 521 03 33
E sales-us@rackmount.it

RACKMOUNT.IT