#### Product Line CP-RACK

Type RM-CP-T5

#### Supported Models CHECK POINT 1530 CHECK POINT 1550

 DIMENSIONS
 1U

 COLOR
 RAL 9005 Black

 PACKING DIMENSIONS
 80 x 520 x 270 mm

 .14 x 20.47 x 10.63 in
 3.14 x 20.47 x 10.63 in

 PRODUCT DIMENSIONS
 44 x 482 x 217 mm

 (height x width x depth)
 1.73 x 18.98 x 8.54 in



## MOUNTING INSTRUCTIONS

- 1. Place the power supply on the rack and tie it down with the 2 zip ties.
- 2. Remove the four rubber feet and two bolts from the front side of the appliance.
- 3. Place your Checkpoint backwards on the rack, connections facing the front and fix the Checkpoint with the bolts on the bottom of the rack and tighten them lightly.
- 4. Lead the low voltage power cable through the large square hole towards the front of the rack and connect it to the power inlet.
- 5. Tie the excess length of the power cable down with the 3rd zip tie.
- 6. Place your CP-Rack in your 19 inch rack.

Please ensure proper ventilation according to the network appliance manufacturer guidelines.

#### PACKAGE CONTENTS

- Qty Description
- 1 CP-Rack
- 3 Zip ties
- 2 Bolts M3x16mm



### Consider the environment, recycle where applicable.

Rackmount.IT rack mount kits are RoHS compliant, developed & manufactured in the Netherlands and made of first quality parts.

In case of problems please contact your reseller or sales@rackmount.it.

Revision 3- 02-10-2020

EMEA Office Nonnenveld 27 4811 HN Breda The Netherlands T +31 76 200 37 40 E sales@rackmount.it WWW.RACKMOUNT.IT US Office 9201 Metric Blvd - Unit A Austin - TX 78758 United States T +1 512 521 03 33 E sales-us@rackmount.it

# RACKYOUNT