**Product Line** 

FP-RACK

Type

RM-FP-T2

## Supported Models FORCEPOINT 330 FORCEPOINT 331

DIMENSIONS 1.3U

COLOR RAL 9005 Black
PRODUCT DIMENSIONS 57 x 482 x 217 mm

(height x width x depth) 2.24 x 18.98 x 8.54 in



## MOUNTING INSTRUCTIONS


- 1. Remove the 2 bolts on the side of your Forcepoint appliance.
- 2. Place your Forcepoint appliance on the rack with the connectors to the front.
- 3. Use the 2 supplied bolts to fixate the Forcepoint appliance.
- 4. Plug in up to 2 power cables and secure the cables with the zip ties on the rack. (detail 1).
- 5. Place your Forcepoint in your 19 inch rack.
- 6. Place the Rackmount.IT front plate **BELOW** the FP-Rack in your 19 inch rack. Together they are 2U high.

Please ensure proper ventilation according to the network appliance manufacturer guidelines.

## PACKAGE CONTENTS

Qty Description

- 1 FP-Rack + front plate
- 2 Zip ties
- 2 Bolts M3x6mm
- 1 Allen Key



Rackmount.IT rack mount kits are RoHS compliant, developed & manufactured in the Netherlands and made of first quality parts.

In case of problems please contact your reseller or sales@rackmount.it.

Revision 2 - 18-08-2020

EMEA Office Nonnenveld 27 4811 HN Breda The Netherlands T +31 76 200 37 40 E sales@rackmount.it WWW.RACKMOUNT.IT US Office 9201 Metric Blvd - Unit A Austin - TX 78758 United States T +1 512 521 03 33 E sales-us@rackmount.it

