## Product Line FORTIRACK

Type RM-FR-T20

## Supported Models FORTIGATE 90G FORTIGATE 91G

DIMENSIONS 1U

COLOR RAL 9003 White
PRODUCT DIMENSIONS 44 x 482 x 217 mm

(height x width x depth) 1.73 x 18.98 x 8.54 in



## MOUNTING INSTRUCTIONS

- 1. Remove the 4 rubber feet from the bottom of the FortiGate.
- 2. Place up to two appliance backwards on the rack & fix the appliance with the 2 bolts from the bottom and tighten it lightly.
- 3. Place up to 4 power supplies on the extension rack.
- 4. To install the power supplies, put the zip ties through the designated holes, place the power supplies on the rack between the zip ties and tighten firmly.
- 5. Tie the excess length of the power cable down with the 3rd zip tie.
- 6. Slide the extension part into the rack as shown on the picture and fix the two parts with two washers and M3x6mm bolts.
- 7. Place your FortiRack in your 19 inch rack.

Please ensure proper ventilation according to the network appliance manufacturer guidelines.

## PACKAGE CONTENTS

Qty Description

- 1 FortiRack
- 1 FortiRack extension part
- 12 Zip ties
- 6 Bolts M3x6mm
- 2 Nut



Consider the environment, recycle where applicable.

Rackmount.IT rack mount kits are RoHS compliant, developed & manufactured in the Netherlands and made of first quality parts.

In case of problems please contact your reseller or sales@rackmount.it.

Revision 1 - 27-10-2023

EMEA Office Nonnenveld 27 4811 HN Breda The Netherlands T +31 76 200 37 40 E sales@rackmount.it

WWW.RACKMOUNT.IT

US Office 9201 Metric Blvd - Unit A Austin - TX 78758 United States T +1 512 521 03 33 E sales-us@rackmount.it

